


# MCA 4030

4 CHANNEL 100V LINE POWER AMPLIFIER



- Configurations possible:  
4 x 30W or 2 x 60W
- Level control on front panel
- Operating mode LED indication
- Emergency control with an output open collector and an input for alarm signal activation command
- Outputs with 3 wires for line, common and emergency
- 19" Rack mounting, 2U high



## MCA 4030

<b>Characteristics</b>	4 Channel 100V Line, 19" rack mounting, 2U high
<b>Continuous power with all piloted channels</b>	4 x 30W (100V) / 2 x 60W (100V)
<b>Frequency response @1 W, -3dB</b>	20Hz~50kHz
<b>Harmonic distortion THD+N</b>	< 0.05%
<b>Signal/noise ratio</b>	85dB (with filter 22Hz~22kHz)
<b>Separation between channels</b>	-66dB @100Hz, -75dB @ 1kHz, -70dB @ 10kHz
<b>Inputs</b>	A and B balanced, with screw connector (B priority)
<b>Input impedance</b>	10 kohm (unbalanced) 20 kohm (balanced)
<b>Input sensitivity</b>	0dBu (0.775V) with balanced input, 6dBu (1.5) with unbalanced input
<b>Controls</b>	Volume control for each channel
<b>Indicators</b>	Visual LED indicators for each channel
<b>Output connector type</b>	Faston connectors
<b>VAC power supply</b>	100V/230V - 50Hz/60Hz with internal power supply unit
<b>Absorption</b>	300W (@ max power with music signal)
<b>Operating conditions</b>	-20°C~40°C with max. humidity <90%
<b>Protections</b>	Thermal, short circuit, soft start
<b>Weight</b>	7kg
<b>Dimensions</b>	482 x 88 x 220mm (2U rack)